

6820EVS

Emergency Voice System and Fire Alarm Control Panel

The 6820EVS is a fire alarm control panel (FACP) and emergency mass notification system conveniently integrated and housed in one panel, and meets the requirements for mass notification as described in UL 2572. It can be configured to achieve an overall point capacity of up to 1,110 points and connect up to 17 panels in a single communications link.

It has one built-in signaling line circuit (SLC), which can support 159 (SK) System Sensor® sensors and 159 SK modules or 127 (SD) Hochiki® devices per loop. To increase point capabilities, additional SLC loops can be added using the 6815 SLC expander for SK devices or the 5815XL expander for SD devices, increasing the point capacity to a maximum of 1,110 points for SK devices and 635 points for SD devices. Three additional SLCs are needed to reach 1,110 points (SK devices). Four additional SLCs are needed to reach 635 points (SD devices).

The common communications and annunciation link allows up to 17 panels to be connected via copper or fiber optic cable. A designated panel is configured as the communicator for all panels in the link for convenient single-point communications. It also has a built-in, dual-line POTs and IP communicator and optional cellular side-cars.

The emergency communication system operations include an on-board supervised microphone, and all call and non-active call buttons can quickly select all active or all non-active output groups. The system also lets you select an ECS message as a priority over fire.

SWIFT® wireless compatibility provides options for wireless detection through a Class A mesh network. It is ideal for hard-to-wire locations, buildings where new wiring is not allowed, or to provide an easy install

FEATURES & BENEFITS

- Up to 1,110 points for greater design flexibility. Additional SLCs can be added until maximum point levels are reached.
- Connect up to 17 panels on one site with convenient single-point access; compatible with mixed FACP models
- 15 recordable one minute messages can be mapped to eight different EVS buttons
- Built-in USB interface for convenient programming
- Convenient field-upgradeable firmware
- Built-in annunciator with a large 160 character, 4 x40 LCD display, and four programmable buttons minimize time spent executing complex or routine tasks
- 16 built-in speaker group switches; expandable to 32
- Integrated dual path IP and POTs communications and optional cellular side-cars for reliable backup
- Built-in dual phone line and digital alarm communicator/transmitter (DACT) for additional communication options
- Programmable date setting for automatic and Daylight Saving Time changes
- Flexput™ circuits can be individually programmed to function as notification circuits, auxiliary power outputs, or initiating circuits that support both 2- and 4- wire smoke detectors



6820EVS

fire system for new construction projects. SWIFT devices can be combined with other hard-wired 6820EVS compatible devices.

The 6820EVS has a Form C trouble relay, and two programmable Form C relays, along with powerful features such as drift compensation, pre-trouble maintenance alert, a built-in sensor test to comply with NFPA 72 calibration testing requirements, and calibration trouble alert. It supports a variety of devices, including the 6860, 5860, and 6855 remote annunciators, 5824 serial parallel printer interface module (for printing system reports), the 5496 NAC expander, 5895XL power module, and SK or SD devices.

The panel also has four programmable buttons which are ideal for programming simple, complex and routine tasks.

6820EVS Product Information

SIGNAL LINE CIRCUIT (SLC)

The 6815 signal line circuit (SLC) supports multiple device types of SK protocol, while the 5815XL signal line circuit (SLC) supports multiple device types of SD protocol. You cannot mix SD and SK SLC devices on a FACP.

The 6820EVS has one built-in signaling line circuit (SLC) which supports multiple devices. Additional points can be added using up to three 6815 SLC expanders to increase overall capacity to 1,110 maximum points (SK devices) or by adding up to four 5815XL SLC expanders to reach 635 maximum points (SD devices). The number of SLCs which can be used within one system is only limited by point count. (See the Manual for additional information.)

The 6820EVS SLC loops support multiple device types, maintenance alerts, and a built-in sensor test to comply with NFPA 72 calibration testing requirements.

INDICATOR LIGHTS

- **General Alarm (Red):** Flashes if in alarm; solid when alarm is silenced
- **Supervisory (Yellow):** Flashes if a supervisory condition exists; solid when supervisory is silenced
- **System Troubles (Yellow):** Flashes if a trouble condition exists; solid when trouble is silenced
- **System Silenced (Yellow):**
On when an alarm, trouble or supervisory condition has been silenced but not yet cleared
- **System Power (Green):** Flashes for AC failure; solid when power systems are normal

USER INTERFACE

The 6820EVS built-in 4 x 40 annunciator with 160 character LCD display and large easy-to-use tactile touchpad can be used for system operation, programming and

maintenance. It has five LEDs for alarm, supervisory, system trouble, system silenced and system power.

System operations include silencing alarms and troubles, resetting alarms and the display of alarm troubles and memory. The system's non-volatile event history buffer stores 1,000 events for viewing from the built-in or remote annunciator. System operations can be initiated with a mechanical firefighter's key or a valid 4- to 7-digit operator's code.



6820EVS KEYPAD

PROGRAMMING

The 6820EVS system offers several options to simplify and speed-up programming. JumpStart® AutoProgramming minimizes programming required to start a new system. The built-in keypad, or the 6860, 5860 or 6855 remote annunciators give you on-site access to current system programming. You can also program the system using the Honeywell Fire Software Suite (HFSS), which is Windows® based.

SOFTWARE TOOLS

SKST: Silent Knight Selection Tool provides the installer or design architect with a Windows® software system configuration tool to create a detailed Bill of Material (BOM) and battery calculations.

HFSS: Honeywell Fire Software Suite provides communication and panel programming, detector status, event history and additional data. Requires a Windows-based computer.

ADDITIONAL INFORMATION

Twisted-unshielded pair wire is recommended.

The 6820EVS also has 13 preset notification cadence patterns (including ANSI 3.41).

AGENCY LISTINGS AND APPROVALS

NFPA 13, NFPA 15, NFPA 16, NFPA 70, NFPA 72: Central station; remote Signaling; Local Protective Signaling Systems; Auxiliary Protected Premises Unit; Water Deluge releasing service. Suitable for automatic, manual, waterflow, sprinkler supervisory (DACT non-coded) signaling services.

UL Listed; **CSFM** 7165-0559:0500; **FDNY** COA# 6249; **FM** approved; **Seismic** (CA) (pending)

UL listed for Continuous or ANSI 520Hz speaker tones that meet NFPA 72 Low Frequency Signal Requirements for Sleeping Areas when used with the EVS-INT50W or EVS-100W amplifiers and compatible speakers

ORDERING INFORMATION

6820EVS: Emergency Communication System with FACP. (Red cabinet).

COMPATIBLE ANNUNCIATORS

6860: 4x40 LCD remote fire annunciator (4 lines and up to 160 characters) per system; four programmable buttons

5860: 4x20 LCD remote fire annunciator. 5860 is gray; 5860R is red

6855: 4x20 LCD remote fire annunciator

5865-3 or 5865-4: LED annunciators can display up to 30 LEDs (15 red and 15 yellow). The 5865-4 has key switches for silence and reset, and a system trouble LED.

5880: The 5880 LED / IO module has 40 programmable LED outputs and eight supervised dry contact inputs which are useful for custom applications. You can use up to eight 5880 modules on one control panel for maximum flexibility.

6820EVS COMPATIBLE DEVICES AND ACCESSORIES

See the data sheets listed below for a complete listing of the SK, SD or SWIFT devices.

53623: SK Devices Data Sheet

53624: SD Devices Data Sheet

350614, 350616 & 350618: SWIFT wireless devices

For a complete and current listing of compatible devices and accessories go to www.silentknight.com

Important: You cannot mix SK and SD devices in the same fire alarm system.

SK COMPATIBLE ADDRESSABLE DEVICES

SK-ACCLIMATE: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature

SK-BEAM: Reflected beam smoke detector without test feature

SK-BEAM-T: Reflected beam smoke detector with test feature

SK-CONTROL: Supervised control module

SK-CONTROL-6: Six circuit supervised control module

SK-DUCT: Photoelectric duct smoke detector with extended air speed range

SK-FIRE-CO: Four criteria fire and carbon monoxide detector

SK-HEAT: Fixed thermal detector (135°F)

SK-HEAT-ROR: Fixed rate of rise detector (135°F)

SK-HEAT-HT: Fixed high temperature thermal detector (190°F)

SK-ISO: Fault isolator module

SK-MINIMON: Mini monitor module

SK-MONITOR: Monitor module

SK-MONITOR-2: Dual input monitor module

SK-MON-10: 10 input monitor module

SK-PHOTO: Photoelectric smoke detector

SK-PHOTO-T: Photoelectric smoke detector with thermal (135°F fixed temperature)

SK-PHOTO-R: Photoelectric detector with remote test capability

SK-PULL-SA: Addressable single action pull station

SK-PULL-DA: Addressable dual action pull station

SK-RELAY: Addressable relay module

SK-RELAY-6: Addressable Six relay control module

SK-RELAYMON-2: Addressable Dual relay/monitor module

SK-ZONE: Addressable zone interface module

SK-ZONE-6: Six zone interface module

B210LP: 6" mounting base

B501: 4" Flangeless mounting base

B200S: Intelligent sounder base

B200S-LF: Low-frequency intelligent sounder base

B224RB: Relay base

B224BI: Isolator base

SD COMPATIBLE ADDRESSABLE DEVICES

SD505-6AB: Addressable 6" base

SD505-6IB: Addressable 6" short circuit isolator base

SD505-6RB: Addressable 6" relay base

SD505-6SB: Addressable 6" sounder base

SD500-AIM: Addressable input module (switch input)

SD500-ANM: Addressable notification module

SD500-ARM: Addressable relay module

SD505-DTS-K: Remote test switch and LED indicator for the SD505-DUCTR

SD505-DUCT: Addressable Duct Smoke Detector.

SD505-DUCTR: Addressable Duct Detector housing with relay base.

SD505-HEAT: Absolute temperature heat detector. Trip point range from 135°F–150°F (0°C–37°C).

SD500-LIM: Addressable Line isolator module

SD500-MIM: Addressable Mini input monitor module (switch input)

SD505-PHOTO: Photoelectric smoke detector

SD500-PS/-PSDA: Addressable Single or dual action pull station

SD500-SDM: Addressable smoke detector module

AUDIBLE/VISIBLE DEVICES

These AV devices are all 2-wire. Color: "R" indicates red; "W" denotes white. For a complete listing of Silent Knight AV devices go to www.silentknight.com.

CHSRL/CHSWL: Wall chime/strobe

CHSCL/CHCWL: Ceiling chime/strobe

CHRL/CHWL: Wall chime

HRL/HWL: Wall horn

P2RL/P2WL: Wall horn/strobe

PC2RL/PC2WL: Ceiling horn/strobe

SRL/SWL: Wall strobe

SCRL/SCWL: Ceiling strobe

SPSCL/SPSCWL: Ceiling speaker/strobe

SPSRL/SPSWL: Wall speaker/strobe

SPRL/SPWL: Wall speaker

SPCRL/SPCWL: Ceiling speaker

SWIFT WIRELESS DEVICES

SWIFT is only compatible with System Sensor (SK) devices. It is not compatible with Hochiki (SD) devices.

WSK-WGI: Wireless Gateway

WSK-PHOTO: Wireless Photoelectric smoke detector

WSK-PHOTO-T: Wireless Multi-criteria photoelectric smoke detector with thermal detection (135°F fixed temperature) and B510W 4" base

WSK-HEAT: Wireless Heat, (135°F fixed temperature) and B510W 4" base

WSK-HEAT-ROR: Wireless heat, ROR (135°F fixed temperature) and B510W 4" base

WSK-MONITOR: Wireless monitor module

WSK-RELAY: Wireless relay module

W-USB: SWIFT Tools USB transceiver used for communication with SWIFT devices

SBUS ACCESSORIES

6815: Each Single Line Circuit allows for an additional 159 SK modules and 159 SK sensors to be added to the system—up to 1,110 total points. Supports System Sensor SK devices only.

5815XL: Each Single Line Circuit provides an additional 127 SD devices to be added to the system—for a maximum of 635 points. Supports SD devices only.

5496: A 6 amp notification power expander with four power-limited notification appliance circuit outputs.

5883: Relay Interface. Provides 10 Form C relays.

5824: Serial/Parallel Printer Interface Module for printer connection.

5895XL: Power Supply with six Flexput™ circuits, and two Form C relays. Max. 16 per system.

5815RMK: Remote mounting kit. Dimensions 10 3/8"W x 10-3/16"H x 3"D

EVS ACCESSORIES

EVS-50W: 50 Watt Amplifier*

EVS-125W: 125 Watt Amplifier*

EVS-100W: 50/100 Watt Amplifier*

EVS-100WBU: External Backup Amplifier

EVS-INT50W: 50 Watt Internal Amplifier

EVS-CE4: Circuit Audio Expander

EVS-SW24: 24 Switch Expander

EVS-VCM: Voice Control Module

EVS-LOC: Local Operator Console**

*Support for up to four amplifiers; 500W maximum. Each amplifier has four built-in speaker circuits expandable to eight.

** Supports up to four EVS-LOCs

COMMUNICATION OPTIONS

CELL-CAB-SK: Cellular communicator, metal enclosure with lock/key*

CELL-MOD: Cellular communicator, plastic enclosure*

*Sole path, powered by panel.

IPGSM-4G: Dual path fire alarm communicator, cellular and/or IP (primary or backup, selectable)

SK-IP-2: Remote reporting via the Internet. Requires a VisorAlarm® receiver at the central station

6820EVS Accessories and Technical Specifications

MISC. ACCESSORIES

SK-NIC: Network Interface Card. Provides a common communications link for the 6820EVS. (Panels cannot be linked together for peer-to-peer networking).

SK-NIC-KIT: Installation Accessory Kit

SK-FML: Fiber-Optic Multi Mode, transmitter and receiver

SK-FSL: Fiber-Optic Single Mode RBB: Remote battery box accessory cabinet or batteries that are too large to fit in the FACP cabinet. Dimensions: 16" W x 10" H x 6" D (406mm W x 254mm H x 152mm D).

SK-SCK: Seismic Compliance Kit used to securely fasten batteries to the fire panel.

PHYSICAL

Overall Dimensions: 21.59"W x 28.1"H x 5.05"D

Shipping Weight: 50 lbs.

Color: Red

ENVIRONMENTAL

Operating Temperature: 32°F to 120°F (0°C to 49°C)

Humidity: 0 to 93% relative humidity (non-condensing)

ELECTRICAL

6820EVS Primary AC: 120AC @ 60Hz, 3.3A Total Accessory Load: 6A @ 27.4VDC power-limited

Standby Current: 190mA

Alarm Current: 250mA

Battery Charging Capacity: 7 to 35AH

Battery Size: 18AH max. allowed in control panel cabinet. Larger capacity batteries can be housed in RBB accessory cabinet.

Six conductor wiring: 4 SBUS and 2 Voice Bus

FLEXPOT CIRCUITS

Six programmable circuits which can be programmed individually as:

Notification Appliance Circuits: 3A @ 27.4VDC per circuit, power-limited (with a panel maximum current of 6A)

Auxiliary Power Circuits: 3A @ 27.4VDC per circuit, power-limited

Initiating Circuits (Circuits 5 and 6 Only): 100mA @ 27.4VDC per circuit, power limited

Supports Class B (Style 4) and Class A (Style 6) configuration for SLC, SBUS, and Flexput circuits

WIRING: See the product manual for wiring details

For a complete listing of all compliance approvals and certifications, please visit www.silentknight.com.

Microsoft, Windows, and the Windows Logo are registered trademarks or trademarks of Microsoft Corporation.

Silent Knight®, Honeywell® and SWIFT® are registered trademarks and Flexput™ is a trademark of Honeywell International, Inc

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

For Technical Support, call 800-446-6444.

For more information

Learn more about Honeywell Silent Knight and other products by visiting www.silentknight.com

Honeywell Silent Knight

12 Clintonville Road
Northford, CT 06472
800-328-0103

351606 | A | 11/17
© 2017 Honeywell International Inc.

Honeywell